

CT22 Function-Key Programming Guide

Step 1: Download the utility's installation file "AKU_V1_2_5": https://www.dropbox.com/s/lk32l4scm0d2zgy/AKU_V1_2_5.exe?dl=0

Step 2: Double Click "AKU_V1_2_5.exe" to install the program.

Step 3: Run the utility "Advanced Keyboard Utility". It can be found under Start button.



Step 4: Indicator on the top right corner of the utility should be green to indicate that the function keys are ready to get programmed.

S Advanced Keyboard Utility (1.2R5) - (New)	- 🗆 X
File View Tools Help	\sim
🗅 🖼 🖬 🕨 🕲 🖉	()
К	eyboard
Information	Repeat Rate
Part No.	 Layer #1 (Base)
OS Language:	C Layer #2
English V	Layers Information
-	
	—
Undate Bestore Connect	Onen Save Exit
Device Found	PA-12/23 RUM-11816 V1.0R1

Following Steps show how to programming the top functional key "F1" as "Alt" + "F4"

Pioneer

Step 5: Select the function key on the top to program

Advanced Keyboard Utility (1.2R5) - (New) File View Tools Help	- • ×
К.	eyboard
Internation Part Na 3K RR00 OS Lorgage English	Repeat Rate C Layer #1 (Base) C Layers Information
Update Restore Connect	Open Save Exit
Device Found	PA-12723 R0M-11816 V1.0R1

- Step 7: 1) Click the keyboard to start the programming step
 - 2) Click letter "Alt" and "F4"
 - 3) Confirm "Alt" and "F4" is going to be programmed to the function key
 - 4) Click the "Apply" button
 - 5) Close the "Key Definition" window

6) Click "Update" button and then select "Update selected key". To update all keys, select "Update all Keys" button.

S Advanced Keyboard Utilit File View Tools Help	y (1.2R5) - (New)			-		×		
						_		
		Keyboard						
Part No.	Repeat Rate							
3K-FN001	(* Layer #1 (Base)							
OS Language:	C Layer #2							
English	•	Layer	s Information	11	_	=		
						>	- 4	
Key Definitio							5	
(LAID (F4)-2								
							_	
Eso F1 F2 F3 F4 F5 F	76 F7 F8 F9	F10 F11 F12	PtSo ScLk	Brk		Lay	erLock	
1 1 2 3 4 5 ° 6 8		- Backspace	Ins How	e PgOp	Num	1 .	·	
Tab Q W E B T Y	UIOP	11.	Del End	PgDn	7	8 9		
CapsLock A S D F G H	J K L	Enter			4	5 6		
Shiét 🚽 🖌 🤈 V B	м м с >	?] Shiêt	Оp		1	2 3		
Cul 👷 Alt	Alt W	Menu App Cul	nu App Cul Left Down Bi		0		- Ent	
Keyboard/Keypad Special Keys #1 Speci	al Keys #2	Clear	Definition	1	Cancel		Anolu	
			Contrologi		Sancer		- entry	
C Update Restore	Connect	Open	Save		E	at		
Device Found		PA-T2723 R0M-T1816 V1.0R1						
		and the second			1			

Step 8: Close the utility and then test the function key "F1" [End of Document]